




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification 7 : H04B 3/54, H02J 13/00		A1	(11) International Publication Number: WO 00/59127
			(43) International Publication Date: 5 October 2000 (05.10.00)
(21) International Application Number: PCT/GB00/01028 (22) International Filing Date: 27 March 2000 (27.03.00) (30) Priority Data: 9907006.2 27 March 1999 (27.03.99) GB (71) Applicant (for all designated States except US): BINARY ELECTRONICS LIMITED [GB/GB]; 36 Westlecot Road, Swindon, Wiltshire SN1 4HB (GB). (72) Inventor; and (75) Inventor/Applicant (for US only): TAYLOR, Colin [GB/GB]; 36 Westlecot Road, Swindon, Wiltshire SN1 4HB (GB). (74) Agents: DOWNING, Michael, Philip et al.; Fry Heath & Spence, The Old College, 53 High Street, Horley, Surrey RH6 7BN (GB).		(81) Designated States: AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CU, CZ, DE, DK, DZ, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, UA, UG, US, UZ, VN, YU, ZA, ZW, ARIPO patent (GH, GM, KE, LS, MW, SD, SL, SZ, TZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG). Published With international search report.	

(54) Title: SIGNALLING METHOD AND APPARATUS



(57) Abstract

A signalling system is disclosed, comprising a DC power source, a power drain, a cable interconnecting the source and drain, including at least two cores, a signal generator, and a signal receiver; the signal generator being adapted to modulate the power output of the source in dependence on the signal to be transmitted, the signal receiver comprising a comparator adapted to compare the instantaneous power output of the source with a historical average power output thereby to detect the signal. Such a system is reliable in an electrically noisy environment, can be provided at relatively low cost, and can be installed easily and without complexity.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece			TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	NZ	New Zealand		
CM	Cameroon			PL	Poland		
CN	China	KR	Republic of Korea	PT	Portugal		
CU	Cuba	KZ	Kazakstan	RO	Romania		
CZ	Czech Republic	LC	Saint Lucia	RU	Russian Federation		
DE	Germany	LI	Liechtenstein	SD	Sudan		
DK	Denmark	LK	Sri Lanka	SE	Sweden		
EE	Estonia	LR	Liberia	SG	Singapore		

SIGNALLING METHOD AND APPARATUS

The present invention relates to a method and apparatus for transmitting and receiving digital electronic signals. It is particularly, but not exclusively, concerned with handling such signals in electrically noisy environments such as elevators.

Electronic signals are now being introduced into elevators, for a variety of reasons. It is an essential prerequisite of such systems that reliable methods of signalling are available to allow communication between the various electronic units. The capabilities which can be achieved in the electronics system will be held back if communication between units is slow, noisy or unreliable. Elevator systems present a particular difficulty in this respect as they are electrically noisy, with high power switching taking place nearby, and require signals to be transmitted over long distances.

The present invention seeks to provide a signalling system that is reliable in such an environment, which can be provided at relatively low cost, and which can be installed easily and without complexity.

The present invention therefore provides an electronic signalling system, comprising

- a DC power source,
- a power drain,
- a cable interconnecting the source and drain, including atleast two cores,
- a signal generator, and
- a signal receiver;

the signal generator being adapted to modulate the power output of the source in dependence on the signal to be transmitted;

the signal receiver comprising a comparator adapted to compare the instantaneous power output of the source with a historical average power output thereby to detect the signal.

An embodiment of the present invention will now be described, by way of example, with reference to the accompanying Figures, in which;

Figure 1 is a schematic illustration of an elevator system;

Figure 2 shows a schematic circuit of the transmission unit;

Figure 3 shows a schematic circuit of the receiver unit; and

Figure 4 shows the modulated power output during a signal burst.

Since the introduction of electronic systems into the lift industry, means have been sought to enable electronic control and other subsidiary systems to have the following attributes:

- (a) facilitate efficient installation;
- (b) be cost effective in overall terms;
- (c) operate efficiently;
- (d) be robust in installation and operation;
- (e) have high capability and exhibit advanced features.

The lift industry has to date met difficulty in meeting these requirements in a realistic and economic manner. It has proved unable, in many respects, to introduce "best practice" in difficult working environments and where electrical and electronics skills are in short supply.

The present invention seeks to provide a multi-purpose combined power and signalling system that meets the above requirements, particularly for lift systems. One application of this system provides the power distribution and signalling required for lift position and status indication by means of electronic visual and audio devices. The following example is described in the context of the lift industry but the principle could be applied usefully to many industrial applications.

A principal difficulty is the large number of wires previously required to connect position indicators. Typically one wire is required to enable the lift position to be indicated on position indicators; at best this was reduced to a binary or grey code equivalent. Signalling and power returns add still further difficulties. The overall result was complicated wiring and vulnerability to mis-operation due to non-ideal electrical factors, compounded by frequent failure due to incorrect installation.

Pre-existing industrial signalling solutions such as RS485 are insufficiently forgiving in installation and operation.

The combined power and signalling system described below enables both the transmission of power and signalling over one pair of wires. These wires can be ordinary 2-core mains wire rated to take the peak current of all the connected devices.

By way of context, Figure 1 shows a schematic illustration of an elevator system adopting the present invention. An elevator car 10 travels within an elevator shaft 12 between floors 14, 16, 18, etc. Each floor has the door such as that shown at 20, which corresponds to a door 22 within the elevator car 10. The doors 20 and 22 are suitably aligned when the elevator car 10 is correctly positioned. The elevator car 10 is suspended on an elevator cable 24, which is raised and lowered via a suitable electric motor (not shown). A cable 26 is suspended within the shaft and attaches to the elevator car 10 on a lower edge thereof. The cable 26 is sufficiently long to be suspended from the top of the shaft 12 and travel to the base thereof, before being connected to the elevator car at its lowest position via a short loop immediately below the elevator car 10. Thus, as the elevator car 10 ascends, the cable is pulled upwards with the car.

Each system includes a power supply encoder (one per system), located in the lift controller, and a receiving device (one or more per system), located at each landing and lift car.

The power supply encoder is shown in figure 2. Its function is to provide a source of unregulated, smoothed direct current power (V_{in}). An N-channel power mosfet 100 is then used to modulate this power supplied at 102 which is supplied to the receiving devices via output 104. From this, the connected receiving devices derive both power and signalling information.

The method of power modulation employed is 100% amplitude modulation. This requires that an N-channel power mosfet, optimised for 5 volt gate working, is switched completely on and off by the serial output of a microcontroller. The gate of this mosfet 100 is connected by resistor 106 between the serial input 108 and the gate thus allowing a small CR time constant to be imposed on the switching of the transistor, limiting the dv/dt of the amplitude modulation waveform and thereby reducing EMC propagation. By employing 100% amplitude modulation, power dissipation is minimised in the power mosfet device, allowing (e.g.) a TO220 package device to switch over 10 Amperes as the device spends a minimum of time in its linear region.

Short bursts of high-speed data ensure that the mean duty of the supplied voltage is greater than 90%, as during non-signalling periods (i.e. most of the time) 100% duty is supplied.

A discharge resistor 110 allows the output voltage to return to V_{in} between bursts.

Thus, two outputs are provided, in the form of a switched negative 104 and an unswitched output of V_{in} at 112.

There are a number of types of receiving devices, such as digital displays and speech units. Each incorporates a demodulator incorporating a means for (i) storing energy during power discontinuity (signalling bursts); (ii) demodulating the received modulated power; (iii) line discharge during modulation. Beyond these units, the nature of the receiving device is essentially irrelevant to the invention.

Storing of energy during power discontinuity (i.e. signalling bursts) is achieved by charging a capacitor 200 (C_x) when power is present on the input lines 202, 204. This capacitor is prevented from discharge, by routing the charging path via a power diode 206 (D_c). Thus when the received voltage V_R is less than that on the capacitor there is no external current flow. The charge on the capacitor 200 (C_x) provides a power output at 208, 200 for the device during signalling bursts and the capacitor is sized accordingly.

Demodulation of the incoming power to each receiving device is achieved by means of a comparator 212. This comparator is connected so that one input 214 is derived from the capacitor C_x , thus establishing itself at voltage proportional to the mean incoming voltage, whilst the other input 216 of the comparator is derived from the incoming signal prior to the charging diode (D_c), and reflects the instantaneous voltage on the line. A small amount of hysteresis is established to minimise the effect of noise. The output 218 (V_s) of the comparator 212 is passed to the serial data input of the receiving device microcontroller, which in turn decodes the data present on the incoming modulated power signal.

The inputs 214, 216 to the comparator are in fact set at a simple fraction of the received voltage V_R and the output voltage V_s by way of potentiometer bridges. Thus, the input 216 detects the received voltage V_R after division by resistors 222 and 224 arranged as a potentiometer across V_R . Likewise, the input 214 detects V_s by way of resistors 226 and 228 arranged as a potentiometer across V_s . The resistors 222, 224, 226 and 228 can be selected at suitably high values to limit the current drawn from capacitor 200.

When the encoder power mosfet device is switched off during signalling bursts, resistors (R_d) 110 and 220 at each node provide a means of discharging the

line capacitance, enabling a suitable waveform to be presented to the demodulation circuitry. These resistors (Rd) 100 and 200 are chosen to enable unit length discharge of the line to take place during a power discontinuity. These resistors are chosen to optimise the discharge time, thus reducing EMC emissions whilst allowing adequate signalling speed.

Figure 4 shows the wave form at 104 of Figure 2 during a signalling burst. It will be appreciated that at times when no signal is being passed, 104 will provide a zero voltage reference as compared to the modulated voltage at 112. During signal bursts, mosfet 100 becomes non-conducting and the voltage at 104 rises to the regulated input voltage. Thus, during a signal period such as that shown at 300, the voltage briefly rises to V_{in} before dropping back to substantially zero at 302.

The pulses can be of any width or pattern of widths as required by the signalling method chosen.

Whilst a voltage pulse is taking place, the voltage on the capacitor 200 at the receiving unit will of course slowly decline. This is indicated by the dotted line 304 on figure 4, showing that even allowing for reasonable current consumption by the receiving unit, an adequate voltage difference is maintained to allow the comparator 212 to detect a signal, provided that the capacitor 200 is an adequate rating and the pulses are sufficiently short.

For the sake of completeness, the detailed specifications of the parts appearing in Figures 2 and 3 are given below. However, it is to be understood that the invention is not limited to the specific values presented herewith by way of example;

Figure 2 - Encoder Power Switching Circuit

100

Part 100 IRLZ24 is an n-channel power mosfet optimised for working at 5 Volt TTL gate voltage. It is able to switch DC currents in excess of 12 amperes at voltages greater than 50 Volts.

102

Point 102 is the power supply input, which for this application is a smoothed but unregulated DC voltage between 9 and 40 Volts DC.

104

Point 104 is connected to the drain of the power mosfet (100) and is the switched negative line of the 2-wire power/signalling line. When the power mosfet device (100) is switched on and current flows this point is substantially at 0 Volts DC and hence maximum voltage appears across the load points 112 and 104. When power mosfet device (100) is switched off during periods of signalling during which gate voltage of device 100 is at 0 Volts and hence switched off, voltage at point 104 rises to V_{in} (102) supply voltage.

106

Component 106 is a 10K resistor which is series with the TTL 5 Volt level issued by the microcontroller serial data output and the gate of power mosfet (100). The purpose of this component is to limit the charge and discharge rise and fall time of the gate. This limits the turn on and turn off rate of change of the mosfet device (100) so as to limit EMC emissions.

108

Point 108 is the serial TTL level output of the microcontroller. In this application the data rate is limited to 9600 bits per second. During signalling bursts this voltage is switched between 0 and 5 Volts, whilst between signalling bursts this point remains at 5 Volts.

110

Component 110 (R_d) is a resistor whose value is typically 1K ohms and rated at 1 Watt. The purpose of this resistor is to discharge the line when mosfet (100) is switched off, so that the rate of change of voltage decay between points 112 and 104 is able to follow more closely that of the voltage decay of the gate of mosfet (100).

112

Point 112 is the positive (non-switched) line of the 2-wire system. This point is always at supply potential (V_{in} point 102).

Figure 3 - Power Separation and Signalling Detector Circuit**200**

Component 200 is an electrolytic capacitor of 33uF rated at 40V. The purpose of this device is to charge capacitor 200 from line via diode (206) when voltage across the 2-wire signalling lines is greater than that across capacitor 200. This provides power continuity during signalling bursts, when instantaneous voltages fall to 0 Volts.

202

Point 202 is the negative 0-Volt, switched input of the receiving device to

powered and signalled over the 2-wire signalling system. Between signalling bursts this point is at 0 Volts, when full supply voltage is being supplied to line from the encoder. During signalling bursts the instantaneous voltages equals that of 204 when encoder power device (100) is switched off.

204

Point 204 is the positive (un-switched) supply input of the receiving device connected to the 2-wire signalling.

206

Device 206 is a 1N4005 power diode rated at 1 Amp. Current flows when the potential across input points 202 and 204 exceeds that across capacitor 200 + 0.7 Volts. When capacitor 200 is fully charged the current passing through diode 206 is the instantaneous current required by the supplied receiving device. During periods of signalling bursts diode 206 prevents capacitor 200 discharging to line.

208

Point 208 is the 0 Volt internal connection to the receiving node. It is the same potential as point 202 and at a potential of $-V_{out}$ with respect to point 210.

210

Point 210 (V_{out}) is the positive internal connection to the receiving node. It is at potential V_{out} which is the instantaneous value of the voltage across device 200, capacitor C_x , with respect to point 208.

212

Device 212 is a single supply comparator that compares voltages 214 and

216, depending on the relative levels present at these points outputs a voltage of either 0 or 5 Volts at 218.

214

Point 214 is the inverted input to the comparator 212. This point is connected to the potential divider 226 and 228 and is set at a potential determined by the ratio of the 2 resistors 226 and 228 and is set at a potential determined by the ratio of the 2 resistors 226 and 228 and the instantaneous 210 (V_s). 214 thus represents a proportion of the internal supply voltage.

216

Point 216 is the non-inverted input to the comparator 212. This point is connected to the potential divider 222 and 224 and is set at a potential determined by the ratio of the two resistors 222 and 224 and the instantaneous voltage 204. 216 thus represents a proportion of the instantaneous voltage at the input of the receiving node.

218

Point 218 is the output of comparator 212. This output voltage is the detected logic level serial data, which is connected to the serial data input of the microcontroller.

220

Device 220 is a resistor of value 2K7 ohms. This resistor contributes the function of discharging the capacitance of the 2-wire power/signalling system.

222

Device 222 is a resistor of value 1K ohms and is part of the potential divider

that derives voltage 216.

224

Device 224 is a resistor of value 10K ohms and is part of the potential divider that derives voltage 216.

226

Device 226 is a resistor of value 470 ohms and is part of the potential divider that derives voltage 214.

300

Point 300 represents part of a signalling burst at the input of one of the signal receiving devices. At this point in time there is 0 Volts across the input terminals 202 and 204 as the encoder/signal generator used to modulate and supply power to line has been turned off and hence the voltage is at supply voltage potential.

302

Point 302 represents part of a signalling burst at the input of one of the signal receiving devices. At this point in time there is V_s (Supply Voltage) across the input terminals 202 and 204 as the encoder/signal generator used to modulate and supply power to line has been turned on and hence the voltage is at 0 Volts supply potential.

Figure 4

Figure 4 represents part of a signalling burst at the input of one of the signal receiving devices (up to 64) across input terminals 202 and 204. Between

signalling bursts this voltage is at maximum supply voltage minus any voltage drops due to line resistance.

It will of course be appreciated that the above described embodiment is purely illustrative of the present invention.

CLAIMS

1. An electronic signalling system, comprising
 - a DC power source,
 - a power drain,
 - a cable interconnecting the source and drain, including at least two cores,
 - a signal generator, and
 - a signal receiver;

the signal generator being adapted to modulate the power output of the source in dependence on the signal to be transmitted;

the signal receiver comprising a comparator adapted to compare the instantaneous power output of the source with a historical average power output thereby to detect the signal.
2. A signalling system according to claim 1 in which modulation of the power output comprises reduction of the output by at least 50%.
3. A signalling system according to claim 1 in which modulation of the power output comprises reduction of the output by substantially 100%.
4. A signalling system according to any preceding claim in which the power output is modulated such that switching takes place over a finite time.
5. A signalling system according to any preceding claim in which the signal receiver determines the historical average by providing the instantaneous power output to an electrical energy store.

6. A signalling system according to claim 5 in which the energy store is a capacitor.
7. A signalling system according to claim 5 or claim 6 in which the power drain is supplied with power by the energy store.
8. A signalling system according to any preceding claim in which a resistive short circuit is placed across the at least two cores of the cable.
9. A signalling system according to claim 8 in which a resistive short circuit is provided adjacent both the signal generator and the signal receiver.
10. A signalling system substantially as herein described with reference to and/or as illustrated in the accompanying Figures.
11. An elevator apparatus comprising an elevator car supplied with power from a fixed source, including a signalling system according to any preceding claim adapted to send data signals to the car.
12. A signalling method in which a power signal is modulated with a data signal such that the power level is significantly reduced on a periodic basis, the power being fed to a receiver unit, the demodulation steps comprising taking a historic average power level and comparing that to the instantaneous power level.
13. A signalling method according to claim 12 in which the power level is reduced by at least 50%.

14. A signalling method according to claim 12 in which the power level is reduced by substantially 100%.
15. A signalling method substantially as herein described with reference to and/or as illustrated in the accompanying Figures.

1/2

Fig 1





Fig 4

2/2




Fig 2




Fig 3

INTERNATIONAL SEARCH REPORT

International Application No

PC1/GB 00/01028

A. CLASSIFICATION OF SUBJECT MATTER
IPC 7 H04B3/54 H02J13/00

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04B H02J

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
------------	--	-----------------------

A	<p>EP 0 380 187 A (FORMULA SYSTEMS LTD) 1 August 1990 (1990-08-01) column 8, line 36 -column 9, line 6 column 9, line 15 - line 23 column 10, line 26 -column 11, line 5 ---</p>	<p>1-9, 11-14</p>
A	<p>EP 0 092 284 A (RADIOTECHNIQUE COMPELEC ;PHILIPS NV (NL)) 26 October 1983 (1983-10-26) abstract -----</p>	<p>1-9, 11-14</p>

☐ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

*** Special categories of cited documents :**

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

- *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- *&* document member of the same patent family

Date of the actual completion of the international search

15 June 2000

Date of mailing of the international search report

10. 07. 2000

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

De Iulius, M

INTERNATIONAL SEARCH REPORT

International application No.
PCT/GB 00/01028

Box I Observations where certain claims were found unsearchable (Continuation of item 1 of first sheet)

This International Search Report has not been established in respect of certain claims under Article 17(2)(a) for the following reasons:

1. ☐ Claims Nos.:
because they relate to subject matter not required to be searched by this Authority, namely:
2. ☒ Claims Nos.: 10,15
because they relate to parts of the International Application that do not comply with the prescribed requirements to such an extent that no meaningful International Search can be carried out, specifically:
The claims 10,15 refer to figures. This is not allowed by the rule 29 (6)
3. ☐ Claims Nos.:
because they are dependent claims and are not drafted in accordance with the second and third sentences of Rule 6.4(a).

Box II Observations where unity of invention is lacking (Continuation of item 2 of first sheet)

This International Searching Authority found multiple inventions in this international application, as follows:

1. ☐ As all required additional search fees were timely paid by the applicant, this International Search Report covers all searchable claims.
2. ☐ As all searchable claims could be searched without effort justifying an additional fee, this Authority did not invite payment of any additional fee.
3. ☐ As only some of the required additional search fees were timely paid by the applicant, this International Search Report covers only those claims for which fees were paid, specifically claims Nos.:
4. ☐ No required additional search fees were timely paid by the applicant. Consequently, this International Search Report is restricted to the invention first mentioned in the claims; it is covered by claims Nos.:

Remark on Protest

- ☐ The additional search fees were accompanied by the applicant's protest.
- ☐ No protest accompanied the payment of additional search fees.

FURTHER INFORMATION CONTINUED FROM PCT/ISA/ 210

Continuation of Box I.2

Claims Nos.: 10,15

The claims 10,15 refer to figures. This is not allowed by the rule 29 (6)

The applicant's attention is drawn to the fact that claims, or parts of claims, relating to inventions in respect of which no international search report has been established need not be the subject of an international preliminary examination (Rule 66.1(e) PCT). The applicant is advised that the EPO policy when acting as an International Preliminary Examining Authority is normally not to carry out a preliminary examination on matter which has not been searched. This is the case irrespective of whether or not the claims are amended following receipt of the search report or during any Chapter II procedure.

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/GB 00/01028

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
EP 0380187	A	01-08-1990	AT 101279 T	15-02-1994
			AU 614444 B	29-08-1991
			AU 4466389 A	08-03-1990
			AU 613809 B	08-08-1991
			AU 4466489 A	08-03-1990
			AU 614197 B	22-08-1991
			AU 4466689 A	15-03-1990
			AU 599616 B	26-07-1990
			AU 6599286 A	02-06-1987
			CA 1285627 A	02-07-1991
			CA 1285629 A	02-07-1991
			CA 1285630 A	02-07-1991
			CA 1303177 A	09-06-1992
			DE 3689612 D	17-03-1994
			DE 3689612 T	13-10-1994
			EP 0226322 A	24-06-1987
			WO 8703100 A	21-05-1987
			JP 63501315 T	19-05-1988
			NZ 218180 A	29-01-1990
			NZ 230789 A	29-01-1990
			NZ 230790 A	29-01-1990
			NZ 230791 A	29-01-1990
			PH 25367 A	13-05-1991
			US 4894952 A	23-01-1990
			US 4910464 A	20-03-1990
			US 4864296 A	05-09-1989

EP 0092284	A	26-10-1983	FR 2525417 A	21-10-1983
			DE 3373857 D	29-10-1987

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☒ FADED TEXT OR DRAWING
- ☐ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☐ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.